<u>REPLACEMENT CLAIMS</u>

Cancel claims 4-6 and 15-17.

1. (Amended) A chip rate base band processor which receives digital information containing

symbol information and provides a symbol output, comprising:

an input memory which stores the digital information;

a data PN code buffer;

a pilot PN code buffer;

a pilot multiplier having a first input coupled to the pilot PN code buffer, a second input coupled to the input memory, and an output;

a data multiplier having a first input coupled to the data PN code buffer, a second input coupled to the input memory, and an output;

a pilot correlator having an input coupled to the output of the first multiplier, and an

output;

a pilot memory coupled to the pilot correlator;

a channel estimator coupled to the pilot memory;

a peak detector coupled to the pilot memory;

a data correlator coupled to the data multiplier;

load controller having a first input coupled to the peak detector, a second input coupled to

data correlator, and an output;

a data memory coupled to the load controller;

a phase rotator having a first input coupled to the channel estimator, a second input

coupled to the data memory, and an output; and

a symbol combiner having an input coupled to the phase rotator, and an output which

provides the symbol output.

7. (Amended) In a chip rate base band receiver processor which receives digital information

containing symbol information, wherein each symbol of the symbol information is of a

predetermined time duration, a method comprising the steps of:

storing the digital information;

multiplying a PN code with a first segment, corresponding to a first multi-path and

representative of the predetermined time duration, of the stored digital

information and

3

multiplying the PN code with a second segment, corresponding to a second multi-path and representative of the predetermined time duration, of the stored digital information.

8. (Amended) In a chip rate base band receiver processor which receives digital information containing symbol information, wherein each symbol of the symbol information is of a predetermined time duration, a method comprising the steps of:

storing the digital information; and

successively multiplying a first PN code with a first plurality of segments of the stored digital information, wherein each segment corresponds to a different multi-path is representative of the predetermined time duration.

4